

FIREWIRE CAT5 EXTENDER



Allows you to connect FireWire Device that is up to 120m at S100, 70m at S400 in length by using cost-effectively Cat.5e/6 cable.

Easy setting-up by using a Cat.5e/6 twisted pair cable for connection, without any confusion or difficulty. No configuration necessary like all FireWire compliant hardware. This **FIREWIRE CAT.5 EXTENDER** will work for both 1394a and 1394b signals at speeds up to 400 Mbps.

Specifications:

- One IEEE1394b Bilingual Connector
- One RJ45 Connector
- Works with both PCs, Macs and Linux
- Compatible with 1394a and 1394b standard
- Full Duplex Data Rate at up to 400 Mbps
- Reach up to 120m (S100) and 70m (S400)
- Use standard Cat.5e/6 cables
- Low power consumption : 2.7W (DC 9V/0.3A)
- DC power jack for optional self power
- Operating Temperature : -45°C ~ 70°C
- Compact size : 75 x 57 x 29 mm

1394 Rating	Extending range	
	Cat 5e	Cat 6
S100	120m	130m
S200	100m	110m
S400	70m	90m